


Electronics

Data Sheet

Resistors	Preferred values for resistors (E24) series: 1.0, 1.1, 1.2, 1.3, 1.5, 1.6, 1.8, 2.0, 2.2, 2.4, 2.7, 3.0, 3.3, 3.6, 3.9, 4.3, 4.7, 5.1, 5.6, 6.2, 6.8, 7.5, 8.2, 9.1 ohms etc.																						
Resistor Printed Code (BS 1852)	This code consists of letters and numbers: R means $\times 1$ K means $\times 1000$ (i.e. 10^3) M means $\times 1\,000\,000$ (i.e. 10^6) Position of the letter gives the decimal point Tolerances are given by the letter at the end of the code, $F = \pm 1\%$, $G = \pm 2\%$, $J = \pm 5\%$, $K = \pm 10\%$, $M = \pm 20\%$.																						
Resistor Colour Code	<table> <thead> <tr> <th>Number</th> <th>Colour</th> </tr> </thead> <tbody> <tr><td>0</td><td>Black</td></tr> <tr><td>1</td><td>Brown</td></tr> <tr><td>2</td><td>Red</td></tr> <tr><td>3</td><td>Orange</td></tr> <tr><td>4</td><td>Yellow</td></tr> <tr><td>5</td><td>Green</td></tr> <tr><td>6</td><td>Blue</td></tr> <tr><td>7</td><td>Violet</td></tr> <tr><td>8</td><td>Grey</td></tr> <tr><td>9</td><td>White</td></tr> </tbody> </table> 	Number	Colour	0	Black	1	Brown	2	Red	3	Orange	4	Yellow	5	Green	6	Blue	7	Violet	8	Grey	9	White
Number	Colour																						
0	Black																						
1	Brown																						
2	Red																						
3	Orange																						
4	Yellow																						
5	Green																						
6	Blue																						
7	Violet																						
8	Grey																						
9	White																						
	Tolerance, gold = $\pm 5\%$, silver = $\pm 10\%$, no band = $\pm 20\%$																						
Silicon diode	$V_F = 0.7 \text{ V}$																						
Silicon transistor	$V_{be} \approx 0.7 \text{ V}$ in the on state, $V_{ce} \approx 0.2 \text{ V}$ when saturated																						
Resistance	$R_T = R_1 + R_2 + R_3 + \dots$ series																						
	$\frac{1}{R_T} = \frac{1}{R_1} + \frac{1}{R_2} + \frac{1}{R_3} + \dots$ parallel																						
Capacitance	$\frac{1}{C_T} = \frac{1}{C_1} + \frac{1}{C_2} + \frac{1}{C_3} + \dots$ series																						
	$C_T = C_1 + C_2 + C_3 + \dots$ parallel																						
Time constant	$T = CR, \quad T_{1/2} = 0.69 CR$																						
ac theory	$I_{\text{rms}} = \frac{I_0}{\sqrt{2}}$ $V_{\text{rms}} = \frac{V_0}{\sqrt{2}}$ $X_C = \frac{1}{2\pi f C}$ reactance $X_L = 2\pi f L$ reactance $f = \frac{1}{T}$ frequency, period $f_0 = \frac{1}{2\pi\sqrt{LC}}$ resonant frequency																						

This insert page should not be sent to the examiner

Operational amplifier	$G_V = \frac{V_{\text{out}}}{V_{\text{in}}}$	voltage gain
	$G_V = - \frac{R_f}{R_i}$	inverting
	$G_V = 1 + \frac{R_f}{R_i}$	non-inverting
	$V_{\text{out}} = -R_f \left(\frac{V_1}{R_1} + \frac{V_2}{R_2} + \frac{V_3}{R_3} \right)$	summing
	$V_{\text{out}} = (V_+ - V_-) \frac{R_f}{R_i}$	difference
555 Astable and Monostable	$T = 1.1RC$	monostable
	$t_H = 0.7 (R_A + R_B)C$	astable
	$t_L = 0.7 R_B C$	
	$f = \frac{1.44}{(R_A + 2R_B)C}$	astable frequency
Electromagnetic waves	$c = 3 \times 10^8 \text{ m s}^{-1}$	speed in vacuo

Assembler language microcontroller instructions

Mnemonic	Operands	Description	Operation	Flags	Clock cycles
NOP	none	No operation	none	none	1
CALL	K	Call subroutine	stack <= PC PC <= K	none	2
RET	none	Return from subroutine	PC <= stack	none	2
INC	R	Increments the contents of R	(R) <= (R) + 1	Z	1
DEC	R	Decrements the contents of R	(R) <= (R) - 1	Z	1
ADDW	K	Add K to W	W <= W + K	Z, C	1
ANDW	K	AND K with W	W <= W • K	Z, C	1
SUBW	K	Subtract K from W	W <= W - K	Z, C	1
ORW	K	OR K and W	W <= W + K	Z, C	1
XORW	K	XOR K and W	W <= W \oplus K	Z, C	1
JMP	K	Jump to K (GOTO)	PC <= K	none	2
JPZ	K	Jump to K on zero	PC <= K if Z=1	Z=1	2
JPC	K	Jump to K on carry	PC <= K if C=1	C=1	2
MOVWR	R	Move W to the contents of R	(R) <= W	Z	1
MOVW	K	Move K to W	W <= K	Z	1
MOVRW	R	Move the contents of R to W	W <= (R)	Z	1